



## Confidea T-2D2I

Confidea Tabletop Double Delegate Interpretation Unit



### Description

The Confidea T-2D2I is Televic's tabletop delegate unit for discussion systems combined with simultaneous interpretation, fit for 2 delegates. It combines a slim, contemporary design and excellent intelligibility with effortless ease of use. The unit has 2 channel selectors and two headphone outputs with two volume controls. It allows both meeting delegates to speak, request-to-speak and listen to the speaker in his or her native language. Two OLED information displays indicate the selected channel number, the abbreviated channel language name in ISO format and a volume bar. The units interconnect in daisy chain over Cat 5e Plixus® network cabling. The RJ45 connectors are hidden in the

base of the unit and the cables are held in place by two notches in the unit housing.

### Benefits

The Confidea T-2D2I is a *sleek and stylish solution* and can be set up in the blink of an eye. The input and output connections are *auto-sensing and interchangeable*. As a result, installation is *easy, fast, and straightforward*, making it the ideal system for frequently changing environments. The removable microphone is *immune for mobile phone interference*, so delegates can leave their phones switched on during the meeting. The Confidea T-2D2I is backed by the Plixus® network with redundant

cabling and hot swapping options to ensure *maximum reliability*. Finally, its shielded microphone is immune to mobile phone interference.

## Features

- Built-in high-quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback
- Two microphone On/Off or request-to-speak buttons with a signaling LED on each button
- Two headphone outputs with two volume controls
- Two OLED information displays with selected language and volume bar

## Connectivity

- Screw-lock socket to connect a removable microphone.

<b>D-MIC30SL</b>	<b>71.98.0053</b>
<b>D-MIC40SL</b>	<b>71.98.0054</b>
<b>D-MIC50SL</b>	<b>71.98.0055</b>

- Two RJ 45 connectors for loop through cabling
- Two 3.5 mm stereo jack sockets for headphones
- Plixus-powered

## Software

To fully configure, manage, and use the unit, Televic's CoCon management software is required. The following standard licenses are available:

<b>CoCon Discussion</b>	<b>71.98.1101</b>
<b>CoCon Signage</b>	<b>71.98.1102</b>
<b>CoCon Interpretation</b>	<b>71.98.1107</b>

## Certifications

Region	Certification
Europe	CE

## Specifications

Mechanical	
Material	ABS
Color	Black
Size (mm)	250 (w) × 70 (h) × 80 (d)
Size packed (mm)	285 (w) × 85 (h) × 120 (d)
Weight (g)	880
Weight packed (g)	1000
Electrical	
Voltage	48 VDC
Consumption	< 3.5 W
Speaker Output	
Maximum output power	> 1 W
Frequency response	200-20,000 Hz
Dynamic range	> 90 dB
THD @ nominal level	< 0.1%
Load impedance	8 Ω
Headphone Output	
Maximum output	> 10 mW
Frequency response	22-22,000 Hz
Dynamic range	> 90 dB
THD @ nominal level	< 0.1%
Load impedance	16-32 Ω
Microphone Input	
Nominal input level	-54.7 dBV
Maximum input level	-24.6 dBV
Input impedance	1 kΩ
Dynamic range	> 93 dB
Frequency response	25-20,000 Hz
THD @ nominal level	< 0.1%

All information copyright **Televic Conference**, 2016. Version 1.0, October 2016

—  
 Leo Bekaertlaan 1 · 8870 Izegem · Belgium  
 Tel. +32 51 30 30 45  
 Fax +32 51 31 06 70  
 E-mail: [conference@televic.com](mailto:conference@televic.com)  
 Web: <http://www.televic-conference.com>  
*Televic reserves the right to change this document without notice.*