Artist T115S-DSP

Artist T115S-DSP is single 15" active DSP- controlled subwoofer with front loaded cabinet design and customized SMPS class D amplifier with built in DSP. With the powerful and dynamic performance, Artist T115S-DSP is a good match for Artist T45-DSP.

3 presets are available for Artist T115S-DSP.


Normal - to match with Artist T45-DSP Cardioid F - cardioid usage, for front coverage Cardioid B - cardioid usage, for back coverage

You need to combine Cardioid F and Cardioid B together for cardioid usage.



SPECIFICATION

Net Weight



Dimension(W×H×D):438x600x570mm

FEATURES

- Maximum SPL 136 dB
- Customized driver
- The innovative ETETM waveguide technology can ensure excellent frequency response, to achieve very smooth transitions between HF and LF, which provides precise horizontal coverage and ensures clear and balanced sound for the system.
- Built in DSP with 96kHz signal sampling frequency, 56bit precision
- Class D amplifier
- Advanced cooling system in the driver
- Optimized, compact and light weight cabinet design for easy usage
- Comprehensive accessories for different applications

















SYSTEM CONFIGURATION

■ Artist T45-DSP line array

Active DSP-controlled Compact Subwoofer **Frequency Response** 35Hz-250Hz (-6dB anechoic chamber) **Maximum Calculated** 130dB/136dB SPL/1M(Continuous/Peak) LF Driver Customized 15" driver, 4"voice coil **AMPLIFIER Amplifier Circuitry** Class D Power(RMS standards) 1400W **Frequency Response** 20Hz-20kHz(±0.5dB) (1W 8Ω 2ch) Intermodulation Distortion < 0.05% **Total Harmonic Distortion** < 0.05% **Protection** DC protection, short circuit protection, overheat protection, input overload protection, output overload protection, soft startup protection, overvoltage protection, undervoltage protection **Cooling System** Cooling with fans, air convection **DSP** Processor 96kHz signal sampling frequency, 56bit precision **Presets** Normal, Cardioid F, Cardioid B Crossover Controlled by DSP Output/Input **Signal Input** 1× female XLR **Signal Output** 1× male XI R **Power Input** Power connector **Power Output** Power connector **AC Power Operating Range** 100V~130V or 220V~240V(±10%,50/60Hz) Cahinet **Cabinet Material** CNC made of excellent wood **Cabinet Color** Black is the default color. Contact Audiocenter for customization Dimension(W×H×D) 438x600x570mm

43.0kg